PRODUCT MANUAL

Mercury Slim Ceiling Tilt



ULTRALIFT AUSTRALIA

AUTOMATED AV SOLUTIONS

CAUTION

Safety Warning

Moving Parts:
Do not obstruct operation of mechanism with fingers or any object. Injury or damage could result. If adjusting the limits, do so prior to wiring into control systems.

Risk of Electrocution:
Do not connect any power to the lift until installation is complete.
Attach the display panel after the lift has been properly installed and tested.
Unit operates on a 240V with a current draw of 1A.

Wear a Hardhat:
During installation this product or parts of it may move in unexpected ways.
Wear a hardhat to ensure safety at all times.

Wear Protective Eyewear:
During installation this product or parts of it may move in unexpected ways.
Wear protective eyewear to ensure safety at all times.

Be Prepared:
Organise your mounting hardware and have the necessary tools readily accessible before installation.

Do not expose to extreme temperatures or corrosive materials.
Minimize exposure to the elements.
This will void your warranty and reduce the life of the product.

This product should only be installed by a qualified technician.
It may be illegal to install this product in your region if you are not a licensed technician . Doing so will also void your warranty.

Table of Contents

Parts List	4
Screw Kit	5
Mercury Slim Diagram	6
Pre Installation Preparation	7
Ceiling Cut-Out Sizes	7
1. Installation into Roof Cavity	8-10
2. Mounting the display	11-12
3. Cable management	13
4. Adjusting the limits	14
6. Wiring	
Operating the Device	15
Motor Controller Wiring	16
Specifications	17
Warranty and Returns Policy	18-19

Thank You

Thank you for purchasing this Ultralift product. We are sure you will enjoy this unit for years to come. Before installing, operating or adjusting this product, please read this instruction book carefully and completely.

Parts Checklist

When you receive this product, please do the following to ensure you have all of the needed components included in the package.

- Open the carton & inspect for damage
- Locate the following parts:

- 1 — Ceiling Tilt (Complete with pre-wired IR kit)
- 1 — IR hand held remote control
- 1 — Screw Kit (see next page)

Screw Kit: Mercury Slim

A	M4 Pan Phillips screws (16mm Long) Quantity: 4 For fastening certain Screens to Hanging Rails
B	M5 Pan Phillips screws (16mm Long) Quantity: 4 For fastening certain Screens to Hanging Rails
C	5.3 x 20 x 1.25 Washers Quantity: 8 To fasten Screens to Hanging Rails. For use with: M4x16 Pan Phillips screws (A) - 4 required or M5x16 Pan Phillips screws (B) - 4 required Different Screws (A,B,D,F) are used depending on the screen you have. 
D	M6 Pan Phillips screws (16mm Long) Quantity: 4 For fastening certain Screens to Hanging Rails
E	7.4 x 20 x 1.25 Washers Quantity: 4 For use with M6x16 Pan Phillips screws (D)
F	M8 Pan Phillips screws (16mm Long) Quantity: 4 For fastening certain Screens to Hanging Rails 
G	Cable Ties Quantity: 6 For cable management to keep leads tidy
H	M8 Coach Screw (50mm Long) Quantity: 4 Fastens Mercury to in-ceiling Timber Beams
I	Motor Key Quantity: 1 Used to adjust motor limits.
J	M8 Nuts Quantity: 12 Used with 8mm All Threaded Rod to fasten Mercury to concrete slab inside ceiling
K	M8 Washers Quantity: 12 Used with M8 Nuts (shown left) to fasten Mercury to concrete slab inside ceiling
L	8mm All Threaded Rod (1000mm Long) - To fasten Mercury Slim to concrete slab above ceiling cavity Quantity: 4 
M	End Caps Quantity: 4 Used to conceal Coach Screws (See Page 10) 

Mercury Slim Diagram



Important Warning

It is critical that the tension of the wires on the Mercury remains unchanged.
Changing the tension of the wires **will damage the Mercury** and **void your warranty.**
To ensure the tension remains unchanged from factory defaults, please note the following:

- **NEVER open or close the Mercury lift manually (i.e. by hand).**
  Doing so may reduce the tension in the wires, causing them to bunch up on the tubular motor and prevent the lift from raising or lowering properly. The wire may snap if this is the case.



- **NEVER disconnect wires.**
  Doing so will cause the tension of each wire to become uneven/unbalanced, making the load applied to the lifting mechanism uneven. This can cause the Mercury Lift to malfunction and may cause the wires to snap.

Pre-Installation Preparation

Before Installing

- When choosing your lift, keep in mind variances of the display panel size due to things like speakers on the side, top or bottom. These can increase the size of the lift that you will need. Check that the screen is not larger than the maximum screen size allowed (See specifications at end of this manual).
- After establishing the correct location for the lift and display panel, cut a hole in the ceiling at the size listed on the following page.
- Organise a qualified trades person to frame up the roof to accommodate the Ceiling Tilt so that it can be mounted in the correct position.
- Route AV cables from the source to the roof location where the Lift will be installed.
- Ensure that a double power point has been installed in the roof (or where suitable) so that the Lift and display panel can receive power.
- Before mounting the display panel to the Lift, ensure that it will suit the Lift in relation to dimensions, loading capacity and functionality.
- Read instructions completely before proceeding. Follow instructions carefully. Installation contrary to instructions invalidates warranty.

CAUTION:

- Do not obstruct operation of lift with fingers or any object. Injury or damage could result.
- Check above the ceiling for obstructions (i.e. water pipes, cable and duct work) before beginning installation.
- Do not connect any power to the lift until installation is complete
- Attach the display panel only after the lift has been properly installed and tested.
- Unit operates on a 240V with a current draw of 1A.
- If adjusting the limits, do so prior to wiring into control systems.
- Organise your mounting hardware and have the necessary tools readily accessible before installation.

Ceiling cut-out sizes

- Please refer to the Ceiling Cut-out sizes (CW and CD) in the Specifications table at the end of this manual.

Installation into Roof Cavity (1 of 3)

This is best done with two to three people due to the weight of the lift. The following instructions apply to both a ceiling joist and a slab / suspended ceiling.

CAUTION: The screen should only be fitted to the lift when installation of the Mercury Slim has been completed. Installer must ensure lift is secured in the ceiling.

Preparation:

1. Mark out the ceiling cut out as per sizes on page 4, then cut the hole in the ceiling.
2. Frame up the ceiling joists and hanger rails using a qualified trades person (as per figure on next page).
3. Route the Audio Visual cables to the lift position in the ceiling.
4. A double power point is required in the ceiling to power the Mercury Slim and the display panel. NOTE: Access to the power point in the ceiling is advisable.

Installation—please see over for diagrams:

1. Cut 8mm threaded rod (Screw Kit Part L) to suit the distance from the slab / hanger rails to the Lift fixing points on the top corners of the Mercury Slim. See Fig 1.
2. Fix the pre-cut threaded rod to the slab or ceiling hanger rails as shown in Figure 2 on next page.
3. Fit one M8 nut and washer to each threaded rod.
4. Fit one M8 nut and washer 100mm up from the bottom of the threaded rod.
5. Raise the Mercury Slim unit into the pre-cut hole from the underside. Fit the threaded rod through the top frame of the lift. Fit nuts and washers to suspend the lift as shown in Figure 2 on next page.
6. Adjust nuts until the lower frame sits 1-2mm above the plaster underside. Screw a minimum of four M8 x 50 coach screws through the fixing holes on the inside frame of the Lift, into the pre-built timber support frame. (See Figures 2, 3 and 4). Cover the bolts with the supplied end caps (Screw Kit Part M) as shown in Figure 5.
7. Route the AV cables into the lift as per diagram on page 13 (cable management).
8. Expose the IR eye in a suitable position to achieve line of sight to the remote.
9. Expose double sided tape on loose corflute dust cover and fit to frame.



Figure 1.

Installation into Roof Cavity (2 of 3)



Figure 2



Figure 3

Fasten 4 Coach Screws into Ceiling Joists through holes in the framework.

Installation into Roof Cavity (3 of 3)



Figure 4

Fasten Coach Screws into Ceiling Joists.



Figure 5

Cover coach Screws with white Plastic end caps.

Mounting the Flat Panel Display

1. Connect power to the lift and lower lift using the IR hand held remote
2. Disconnect power to the lift
3. Remove the Mount Rails by loosening the two 5mm locking screws.
4. Fit the rails to the back of the screen and bolt using the four Phillips head screws and washers, as per diagram below, noting the orientation from the top of the screen to the top of the rails.



Mounting the Flat Panel Display (Continued)

5. Lift the display Panel and hook rails onto the lift.
6. Tighten the locking screws to lock the rails into position, ensuring that the screws are tight.
7. Ensure the display panel is mounted centrally



Step 5: Lift display panel And hook rails onto lift.

Step 6: Tighten locking screws to lock the rails into position.

Cable Management

1. Connect cables to the display panel and run down cable management arms as per diagram below. Be sure to allow the extra cable length on the cable management arm bend points.
2. Reconnect power to the lift.

CAUTION: Cables must be securely attached to the frame to avoid pinching of the cables. Raise and lower the lift several times using the IR hand held remote, closely watching the cables to make sure they don't interfere with the lift operation. Please note that the installer is responsible for ensuring the cables do not interfere with the mechanism as the unit raises and lowers.



Adjusting Motor Limits

When adjusting the motor limits use the motor key.

If adjusting the limits, do so prior to wiring into control systems.

1. Lower the Lift using the IR hand held remote.
2. Adjust the motor down limit if required with caution.
3. Raise by adjusting the desired up motor limit.

CAUTION: When setting the motor limits, adjust the Up and Down limits with caution. The Up and Down limits are set in the factory to recommended positions. Minor adjustment may be necessary. In the rare case that the factory settings are slightly out, the down limit may be adjusted with caution. Minor adjustment may be necessary if the weight of your screen or projector has sagged the cable length.



Operating the Device

Motor Controller Specifications

- Input: 220VAC/50Hz ±10%
- Output: 220VAC/2.5Amp
- Maximum motor running time 5 minutes
- Both RF and IR receiver; Dry contact closures.
- External IR Lead; Built in IR Eye.
- 12 Volt trigger input for projectors
- Programmable

Remote Control





Motor Controller Box (Side View)

Hex Codes

UP	0x0B
DOWN	0x43
STOP	0x23

Please Note:

Depending on the device the motor control box is connected to, the codes for UP and DOWN may be reversed.

DO NOT OPEN BOX WITH POWER ON! Please Refer to instructions on inside of Motor Controller Box lid for further instructions.



QUICK PROGRAMMING:
Aim the Remote control unit towards the receiver IR eye (IR1) or to the external IR eye while programming. Please refer to above diagram for the location of the Infrared eye (IR1), push button switch (SW4), & LED light (LED1).

PAIRING REMOTE CONTROL TO RECEIVER:
Press SW4 (LED1 blinks) then press the UP button of the remote control unit.

UNPAIRING REMOTE CONTROL FROM RECEIVER:
Press SW4 (LED1 blinks) then press the DOWN button of the remote control unit.

UNPAIRING ALL REMOTE CONTROLS FROM RECEIVER:
Press and hold SW4 for about 4 seconds until LED1 blinks at faster rate, then release the Button. Then press SW4 again.

REVERSING THE UP-DOWN BUTTON DIRECTION:
Press SW4 (LED1 blinks) then press the STOP button of the remote control unit.

Motor Controller Wiring

The Motor Control box may be connected to Automation systems using IR, 12V trigger, or Contact Relay.



IR Eye (IR1)
Receives Infrared signals from remote control through IR window.

12V Trigger (JP2)

A: NC
B: GND
C: +12V
D: NC

External IR (IR2)
Used to connect a lead to an external IR Eye.
A: +5V
B: IR SIGNAL
F: GND



Dry Contact (DRY1)
Used to connect Motor Controller to Dry Contact.
C: UP
D: STOP
E: DOWN
F: COMMON

Power LED under IR1 (LED1)
Illuminates when Motor Controller is connected to AC Power. White in appearance. Located on PCB surface.

Program Button (SW4)
Used to pair/link remote controls with the Motor Controller.

AC Main Power (CNT1)



L: ACTIVE
N: NEUTRAL
E: EARTH

Motor Cable Terminal (CNT2)



E: EARTH
N: NEUTRAL
L: UP OR DOWN
R: UP OR DOWN

Power Cable

Motor Cable

DO NOT OPEN BOX WITH POWER ON! Please Refer to instructions on inside of Motor Controller Box lid for further installation instructions.



NOTE: PRODUCT DIMENSIONS ARE SUBJECT TO CHANGE

PLEASE CALL US TO CONFIRM DIMENSIONS BEFORE PURCHASING, BUILDING FURNITURE, CUTTING INTO WALLS, CEILINGS OR FURNITURE OR PREPARING FOR INSTALLATION.

Model	Description	Dimensions (mm)				Cutout Size (mm)		Max screen size (mm)		
		H	W	D	O	CW	CD	SD	SW	SH
Mercury Slim 32	Compact screen ceiling tilt 32"	85	1000	710	135	Call us for sizes		30	800	530
Mercury Slim 40	Compact screen ceiling tilt 40"	87	1195	860	148	Call us for sizes		30	1016	660
Mercury Slim 42	Compact screen ceiling tilt 42"	121	1188	874	192	1200	885	58	1018	643
Mercury Slim 46	Compact screen ceiling tilt 46"	100	1251	874	194	1260	883	57	1073	663
Mercury Slim 55	Compact screen ceiling tilt 55"	85	1520	1030	207	1530	1040	30	1336	815
Mercury Slim 60	Compact screen ceiling tilt 60"	82	1531	999	233	Call us for sizes		30	1357	779
Mercury Slim 65	Compact screen ceiling tilt 65"	Dimensions available upon application.								

SEE OVERLEAF FOR A LIST OF SUPPORTED TV MODELS







This work is copyright. Apart from any use permitted under the Copyright Act 1968, no part may be reproduced by any process, nor may any other exclusive right be exercised, without the permission of Ultralift Australia

ULTRALIFT AUSTRALIA
AUTOMATED AV SOLUTIONS
www.ultraliftaustralia.com.au
Phone: +613 9459 0873
Fax: +613 9457 6686
Email: sales@ultraliftaustralia.com.au

Mercury Slim 32-65

Updated: 5/3/13

COMPATIBLE TV SIZES

Mercury Slim 42

MAKE	MODEL	WIDTH	HEIGHT	THICKNESS	WEIGHT
PANASONIC	TH-L42E30A	1002	611	75	15
PANASONIC	TH-L42E3A	1002	611	75	15
PANASONIC	TH-L42DT50Z	958	569	27	11
PANASONIC	TH-L42ET50Z	989	643	36	15.5
PANASONIC	TC-L42ET5	997	604	40	14
PANASONIC	TC-P422ST30	1021	640	71	20
PANASONIC	TC-P42UT50	1009	616	84	17.5
PANASONIC	TC-L42E50	997	604	40	14
PANASONIC	TC-L42E5	997	604	40	14
PANASONIC	TC-L42D30	988	600	33	16
PANASONIC	TC-P42S30	1021	640	71	19
PANASONIC	TC-P42ST30	1021	640	71	20
LG	42LW5700	999	623	30.9	13.4
LG	42LV3730	988	615	30.4	13.3
LG	42LV5500	1012	617	29.9	13.2
LG	42LW6500	1009	622	29.9	13.4
LG	42LM7600	953	566	33.4	12.8
LG	42LE4500	1018	627	29.8	14.2
LG	42CS460	1017	629	76.5	13.5
LG	42LS5700	979	594	35.5	12.7
LG	42LM6200	979	594	35.5	13.1
LG	42LM6700	953	566	33.4	12.6
LG	42LM6410	964	577.7	35.7	12.1
LG	42PT250	987.6	608.9	52.5	
LG	42LK450	1019	631	76.5	
LG	42PA4500	983.6	601.3	58	
LG	42LS4600	979	594	35.5	12.7
SONY	KDL-42EX440983	983	603	75	13.2
HI-SENSE	HL42K316PZL3D	986	600	58	15.5
PHILIPS	42PFL5907	997.2	589	58	58.9
OTHER MODELS			With Max Screen Size of 1018W x 643H x 58D		

Mercury Slim 46

MAKE	MODEL	WIDTH	HEIGHT	THICKNESS
SAMSUNG	UA46ES7500M	1046.8	620.2	29.7
SAMSUNG	UA46ES6200M	1062.8	631.1	46.9
SAMSUNG	UA46ES5500M	1062.8	631.1	46.9
SAMSUNG	UA46ES6600M	1063.2	636.4	43.7
SAMSUNG	UA46ES6800	1070.2	635.6	46.9
SAMSUNG	UA46ES6700M	1070.2	635.6	46.9
LG	47LM6700	1063	627	33.4
SHARP	LC46LE835X	1072	663	41
SHARP	LC46LE830X	1072	663	41
SHARP	LC46LE840X	1073	652	57
OTHER MODELS			with Max Size of 1073x663x57mm	

Mercury Slim 55

MAKE	MODEL	WIDTH	HEIGHT	THICKNESS
LG	55LM6700	1232	723	33.6
LG	55LM6200	1263	754	35.5
LG	55LW9500	1265	760	27.5
SAMSUNG	UA55ES8000M	1230.3	722.3	30.8
SAMSUNG	UA55ES7500M	1238.4	728	29.7
SAMSUNG	UA55ES6200M	1253.7	738	46.9
SAMSUNG	UA55ES6600M	1256.6	743.2	43.7
SAMSUNG	UA55ES6800	1260.8	742.4	46.9
SAMSUNG	UA55ES6700M	1260.8	742.4	46.9
SONY	KDL55HX750	1271	761	60
SONY	KDL55HX850	1274	750	35
SONY	KDL55HX925	1278	771	38
SONY	KDL55HX820	1280	774	27
SONY	KDL55NX720	1281	774	27
OTHER MODELS			with Max Size of 1281x774x60mm	

ULTRALIFT AUSTRALIA
AUTOMATED AV SOLUTIONS
www.ultraliftaustralia.com.au
Phone: +613 9459 0873
Fax: +613 9457 6686
Email: sales@ultraliftaustralia.com.au

Warranty and Returns Policy

At Ultralift Australia Pty Ltd, we take pride in the fact that our products are of the highest quality. Because of this, we offer the following programs to ensure your satisfaction.

ULTRALIFT 2 YEAR WARRANTY

1. The product is warranted for 24 months from the date of invoice. Subject to the conditions of this warranty, Ultralift Australia or an authorised installer will perform necessary service on the product without charge for parts or labour if, in the opinion of Ultralift Australia, the product is found to be faulty within the warranty period.

2. This warranty only applies to Ultralift Australia products when purchased from Ultralift Australia or from an authorised dealer.

3. This warranty only applies if the product has been installed and used in accordance with the manufacturer's recommendations (as noted in the instruction manual) under normal use and reasonable care (in the opinion of Ultralift Australia). The warranty covers normal domestic, commercial or educational use only. It does not cover damage, malfunction, neglect, build-up of dirt or dust, abuse, maladjustment of customer controls, mains supply problems, thunderstorm activity, infestation by insects or vermin, tampering or repair by unauthorised persons (including unauthorized alterations), exposure to abnormally corrosive conditions or any foreign object or matter having entered the product.

4. If warranty service is required you should:
    - Contact your installer for advice on how to rectify the issue.
    - If this does not solve the problem please call Ultralift Australia on 61 3 9459 0873 for advice.
    - If the device requires service, return the product to Ultralift Australia for repair.
    - **Please Note:** Freight and insurance to and / or from the location of the device must be arranged by you. Please ensure that items returned are packed in an appropriate manner.

5. The warranties hereby conferred do not extend to, and exclude, any costs associated with the installation, de-installation or re-installation of a product. This includes costs related to the mounting, de-mounting or re-mounting of any screen, (and any other ancillary devices), delivery, handling, freighting, transportation or insurance of the product or any part thereof or replacement to such installation, deinstallation, re-installation or transit.

Ultralift Australia Pty Ltd
Email: sales@ultraliftaustralia.com.au
Web: www.ultraliftaustralia.com.au
Phone: 61 3 9459 0873 **Fax:** 61 3 9457 6686
10 Vernon Ave, Heidelberg Heights VIC 3081 Australia

ULTRALIFT AUSTRALIA

OUR HASSLE FREE RETURN PROGRAM

Our thirty day return program means you may return your purchase, excluding special orders and/or non stock products, to us should you be dissatisfied with your purchase within thirty days of receipt of the product. You must return the item(s) to us by 2nd day freight, insured for full value, with original packaging, documentation, all manuals and accessories. Freight charges, for delivery and return and related insurance charges, will not be refunded or credited. There will also be a restocking fee of 15% of the purchase price.

CONDITIONS OF RETURNED ITEMS

Do not write on the box. If the box is written on, the returned product will be refused. Be in the original shipping carton with all original packing material. Include all accessories in their original wrapping/packing material. The actual replacement cost for missing items will be deducted from your refund/credit. Include all manuals, warranty information and instructions. The actual replacement cost for missing items will be deducted from your refund/credit.

DEFECTIVE OR D.O.A. PROGRAM

In the case of defective or D.O.A. product(s), no charges will apply. Our Customer Service team must be notified within 30 days of your invoice date if there are any problems with any item(s) upon receipt. Defective or D.O.A. merchandise will be repaired and returned or exchanged for the same make or model.

FOR ITEMS DAMAGED DURING TRANSPORT

Ultralift Australia Pty Ltd endeavours to use reputable carriers, but occasionally shipping damage does occur. Resolving the problem of transit damage or loss depends on the cooperation of all parties. In the event of damage or loss it is imperative that you follow these guidelines:

1. Inspect all shipments upon arrival. If damage or loss is apparent upon delivery, do not accept the goods and do not sign for damaged or missing cartons. If you do accept the goods, keep all packing materials and boxes with the damaged product.
2. Immediately advise Ultralift Australia of all damages or problems with the delivery of goods.

REFUNDS

Established Account:

A full refund will not be issued if the purchaser's account has an open balance. A credit memo will be issued, and credit will be applied first to the invoice on which the products were purchased, then to any other open invoices on the account, beginning with the oldest invoice.

Credit Card / EFT:

All refunds for purchases made by Credit Card/EFT will be issued as a credit to that same account within a reasonable period of time after inspection of returned products.

Cheque:

All refunds for purchases paid by cheque, whether prepaid, C.O.D., or account, will be paid by cheque within a reasonable amount of time, after inspection of returned products.

Ultralift Australia Pty Ltd
Email: sales@ultraliftaustralia.com.au
Web: www.ultraliftaustralia.com.au
Phone: 61 3 9459 0873 **Fax:** 61 3 9457 6686
10 Vernon Ave, Heidelberg Heights VIC 3081 Australia

ULTRALIFT AUSTRALIA

THANKYOU FOR CHOOSING

ULTRALIFT AUSTRALIA

Ultralift Australia Pty Ltd
10 Vernon Ave, Heidelberg Heights VIC 3081 Australia
Email: sales@ultraliftaustralia.com.au
Web: www.ultraliftaustralia.com.au
Phone: 61 3 9459 0873
Fax: 61 3 9457 6686

Member CEDIA